

Description: Full Account Loop Disconnect (EATN Level / CKT Level)

Field	Data Description	Business Rule Entry
LSR Form		
CCNA	Customer Carrier Name Abbreviation	<ZTK>
PON	Purchase Order Number	<Your PON>
VER	Version	<01>
LOCQTY	Location Quantity	<001>
DDD	Desired Date Due	<20120112>
REQTYP	Request Type	AB
SLI	Sub Loop Indicator	S
ACT	Activity	D
AGAUTH	Agency Authorization Status	Y
ACTL	Access Customer Terminal Location	<CLEC CLLI>
LSO	Local Serving Office	<517783>
TOS	Type of Service	<22--> (See Footnote 1)
NC	Network Channel Code	LX-- (See Footnote 2)
NCI	Network Channel Interface Code	02QB5.001 (See Footnote 2)
SECNCI	Secondary Network Channel Interface Code	02DU5.001(See Footnote 2)
INIT	Initiator Name	<Initiator Name>
TEL NO	Initiator Telephone Number	<9192257998>
EU Form		
LOCNUM	Location Number	<001>
NAME	End User Name	<Our Business Rules>
AFT	Address Format Type	<N if normal>
SANO	Service Address Number	<14917>
SASN	Service Address Street Name	<Musketeer>
SATH	Service Address Street Type	<RD>
CITY	City	<Anytown>
STATE	State/Province	<CT>
ZIP	Zip/Postal Code	<25504>
EATN	Existing Account Telephone Number	<5170601122> (See Footnote 3)
LS Form		
LQTY	Loop Quantity	<1>
LOCNUM	Location Number	<001>
LNUM	Line Number	<00001>
LNA	Line Activity	D (See Footnote 3)
ECCKT	Exchange Company Circuit ID	</TXNU/123456//SN>(See Footnote 3)



UNE LSR Order Samples

Loop Disconnect

REQTYP: AB

ACT: D

Description: Full Account Loop Disconnect (EATN Level / CKT Level)

Footnotes:

1. Use appropriate TOS Values for Business or Residence service.
2. Use appropriate NC/NCI/SECNCI where applicable at State/Tariff Level
3. Order by EATN only requires LSR/End User Form and No Loop Service Form. If the EATN is unknown, Order by Circuit can be used. You will provide the Loop Service Form with LNA=D and the ECCKT to be disconnected. The entire account will be disconnected under the EATN even if all ECCKT do not appear on the LS form.